

ASRC39 Series

Size 3920 (10 x 5.2mm)

Automotive Current Shunt Resistors



SRC39 Series Current Shunt Resistors aid precision measurement and high-current applications. A wide range of precision shunts, designed for use with kilowatt-hour meters and other high-current applications where a high level of accuracy is required, is now available from PROSEMI.


Features

- Power rating up to 12 W at 70°C
- Excellent long term stability
- Continuous current load up to 160A at 0.2mΩ
- Halogen free, lead free and RoHS compliant
- AEC-Q200 qualified

Appications

- Power modules
- Frequency converters
- Current sensor for power hybrid sources
- High current for automotive
- Lithium battery protection board





Part Number	Power Rating <i>P</i> 70°C (W)	Resistance Range (mΩ)	TCR (ppm/°C)	Material
ASRC39F/K_I5R0	5	5	±50	FeCrAl/Kama
ASRC39F/K_I4R0	5	4	±50	FeCrAl/Kama
ASRC39F/K_I3R0	5	3	±50	FeCrAl/Kama
ASRC39F/K_I2R0	6	2	±50	FeCrAl/Kama
ASRC39F/K_I1R0	8	1	±50	FeCrAl/Kama
ASRC39M_I1R0	7	1	±50	Manganin
ASRC39M_I0R50	9	0.5	±70	Manganin
ASRC39M_I0R30	10	0.3	±150	Manganin
ASRC39M_I0R20	12	0.2	±200	Manganin

• Applicable temperature range of -55°C to +170°C

Power rating is guaranteed for use an aluminum substrate (MCPCB) Part

• Number definition "_" of Resistance Tolerance




Size 3920 (10x5.2mm)

Automotive Current Shunt Resistors

ASRC39 Series

Dimension




Туре	L	W	Т	Α	р	*Quantity
ASRC39F/K_I5R0	10.0±0.2	5.2±0.4	0.78±0.2	2.2±0.2	0.5±0.1	2500
ASRC39F/K_I4R0	10.0±0.2	5.2±0.4	0.78±0.2	2.2±0.2	0.5±0.1	2500
ASRC39F/K_I3R0	10.0±0.2	5.2±0.4	0.87±0.2	2.2±0.2	0.5±0.1	2500
ASRC39F/K_I2R0	10.0±0.2	5.2±0.4	1.06±0.2	2.2±0.2	0.5±0.1	2500
ASRC39F/ K_ I1R0	10.0±0.2	5.2±0.4	1.66±0.2	2.2±0.2	0.5±0.1	2500
ASRC39M_I1R0	10.0±0.2	5.2±0.4	0.90±0.2	2.2±0.2	0.5±0.1	2500
ASRC39M_I0R50	10.0±0.2	5.2±0.4	1.33±0.2	2.2±0.2	0.5±0.1	2500
ASRC39M_I0R30	10.0±0.2	5.2±0.4	1.87±0.2	2.2±0.2	0.5±0.1	2000
ASRC39M_I0R20	10.0±0.2	5.2±0.4	2.14±0.2	2.2±0.2	0.5±0.1	2000

Storage Conditions

• Temperature: 22~28°C, Humidity: 40~75%

Power Derating Curve






Size 3920 (10x5.2mm)

Automotive Current Shunt Resistors

ASRC39 Series

Soldering Parameters



Wave Soldering: 260°C, 10 seconds max. Infrared Reflow: 260°C, 30 seconds max.

IR Reflow Profile	
Preheat Heat Temperature min (Tsmin) Temperature max(Tsmax) Time (Tsmin to Tsmax) (ts)	150°C 200°C 60 -120 seconds
Average ramp-up rate (Tsmax to Tp)	3°C/second max.
Liquidous temperature (TL) Time at liquidous (tL)	217°C 60 - 150 seconds
Peak temperature(Tp)	260+0/-5°C
Time within 5°C of actual peak Temperature (tp)	10 – 30 seconds
Average ramp-down rate (Tp to Tsmax)	6°C/second max.
Time 25 °C to peak temperature	8 minutes max.

Endurance Test

Iterms	Additional Requirements	Reference	Limits
Temperature Cycling	1000 Cycles(-55°C to +125°C) Measurement at 24±2hours after test conclusion	JESD22 Method JA-104	±0.5%
High Temperature Exposure	1000hrs.@T=125°C.Unpowered. Measurement at 24±2 hours after test conclusion	MIL-STD-202 Method 108	±0.5%
Moisture Resistance	t=24hrs/cycle.Note:Steps 7a & 7b not required. Unpowered.	MIL-STD-202 Method 106	±0.5%
Biased Humidity	1000hrs 85°C/85%RH。 Note: Specif ied conditions: 10% of operating power. Measurement at 24±2 hours after test conclusion	MIL-STD-202 Method 103	±0.5%
Operational Life	Condition D Steady State TA=125°C at rated power. Measurement at 24±2hours after test conclusion	MIL-STD-202 Method 108	±0.5%
Solderability	245°C±5°C,5s+0.5s/-0	J-STD-002C	95% Coverage Min
Vibration	5 g's for 20 min, 12 cycles each of 3 orientations. Note: Use 8"X5" PCB .031"thick 7 secure points on one long side and 2 secure points at corners of opposite sides. Parts mounted within 2" from any secure point. Test from 10-2000 Hz. Measurement at 24±2 hours after test conclusion	MIL-STD-202 Method 204	±0.5%
Resistance to Soldering Heat	260°C±5°C, 10s±1s Measurem ent at 24±2hours after test conclusion	MIL-STD-202 Method 210	±0.5%
ShortTime Overload	5×Rated power for5s Measurement at 24±2hours after test conclusion	MIL-STD-202 Method 301	±0.5%

© 2021 PROSEMI Inc. All Rights Reserved. Specifications and features are subject to change without notice. www.prosemitech.com

The PROSEMI logo, and all other PROSEMI trademarks are the property of PROSEMI Inc. All other trademarks are the property of their respective owners.